

19th of September 2014

URGENT - FIELD SAFETY NOTICE

TYPE OF ACTION:	Recall	
TELEFLEX REFERENCE:	40003032/40003631	
Commercial Name		
HUDSON RCI® Nebulizer Adaptor		
Product Description	Product Description	Lots
NEBULIZER ADAPTOR 028,STERILE,SHELFPAK	031-28	Appendix 2
NEBULIZER ADAPTOR 028,STERILE,SHELFPAK,	031-28F	
NEBULIZER ADAPTOR 033,STERILE,SHELFPAK	031-33	
NEBULIZER ADAPTOR 033,STERILE,JAPANESE	031-33J	
AQUAPAK 728 SW,760 ML W/028 ADAPTOR	037-28	
AQUAPAK SW/EAU STERILE,760 ML W/ADAPTOR	037-28C	
AQUAPAK 728 SW,760 ML W/028 ADAPTOR,FREN	037-28F	
AQUAPAK 733 SW,760 ML W/033 ADAPTOR	037-33	
AQUAPAK 735 HNS,760 ML W/028 ADAPTOR	037-35	
AQUAPAK 739 FNS,760 ML W/028 ADAPTOR	037-39	
AQUAPAK 0.9% NACI,760 ML W/ADAPTOR	037-39C	
AQUAPAK 770 HNS,760 ML W/033 ADAPTOR	037-70	
AQUAPAK 1028 SW,1070 ML W/028 ADAPTOR	041-28	
AQUAPAK SW/EAU STERILE,1070 ML W/ADAPTOR	041-28C	
AQUAPAK 1033 SW,1070 ML W/033 ADAPTOR	041-33	
AQUAPAK 1035 HNS,1070 ML W/028 ADAPTOR	041-35	
AQUAPAK 428 SW,440 ML W/028 ADAPTOR	044-28	
AQUAPAK SW/EAU STERILE,440 ML W/ADAPTOR	044-28C	
AQUAPAK 428 SW,440 ML W/028 ADAPTOR,FREN	044-28F	
AQUAPAK 433 SW,440 ML W/033 ADAPTOR	044-33	
AQUAPAK 435 HNS,440 ML W/028 ADAPTOR	044-35	
AQUAPAK 470 HNS,440 ML W/033 ADAPTOR	044-70	
ADAPTOR,028 NEB,INTL	403128	
ADAPTOR,033 NEB,INTL	403133	
AQUAPAK 728 SW,760 ML W/028 ADAPTOR,INTL	403728	
AQUAPAK 1028 SW,1070 ML W/028 ADAPTOR,IN	404128	
AQUAPAK 428 SW,440 ML W/028 ADAPTOR,INTL	404428	

Dear Customer,

1. Details of affected devices

Teleflex has initiated a voluntary Field Safety Corrective Action for the above listed products.

2. Description of the problem

Teleflex Medical has issued a voluntary recall for the products listed in Appendix 1, due to the possibility that the seals of the adaptor packaging may be creased which may potentially affect packaging integrity. The adaptors are labelled as sterile, and the seal crease may affect the sterility of the adaptor.



3. FIELD SAFETY CORRECTIVE ACTION INSTRUCTIONS:

ADVICE ON ACTION TO BE TAKEN BY MEDICAL STAFF

1. We request that you check your inventory for product within the scope of this field action. Users should cease use and distribution of stock of the affected product batch and quarantine immediately.
2. If you do not have stock in scope of this field action as referred to in above table then mark the according checkbox on the Acknowledgement form (Appendix 2) and return the form to the fax number or e-Mail-address mentioned below.
3. If you have stock from the affected product as referred to in above table, mark the according checkbox on the Acknowledgement form (Appendix 2). Contact customer service by calling the phone number mentioned in Section 6 who will issue you with a return number. Write this return number into the respective field in the Acknowledgement form.
4. Complete 'Appendix 2' for all products in your possession and under control. Return this form immediately to Customer Service.
5. Teleflex (or your local dealer) will issue a credit note upon receipt of the returned affected product.

INSTRUCTION FOR DISTRIBUTORS OF AFFECTED PRODUCT

1. If you are a distributor, provide this field safety notice to all of your customers who have received product in scope of this Field Action. Your customer is then required to complete the acknowledgement form and return this to you.
2. As a Distributor you are required to confirm to Teleflex that you have completed the field activity outlined above. Upon completion of your actions, please forward the completed Acknowledgement Form to Customer Service.
3. Please be aware that all European Economic Area/Switzerland (EEA/CH) and Turkey Member State Competent Authorities in which Teleflex distribute directly will be notified by Teleflex.
4. If you are a distributor and/or have a reporting responsibility within or outside the EEA/CH/TK area, please notify your local Competent Authority of this action. Please forward the notification and all communication with your local competent authority to Teleflex.

4. Teleflex

Teleflex informs all customers, employees of Teleflex and distributors on this Field Action.

5. Transmission of this Field Safety Notice

This notice should be passed on to all persons who need to be aware within your organization or to any organization where the potentially affected devices have been transferred. Please consider end users, clinicians, risk managers, supply chain/distribution centres etc. in the circulation of this notice.

Maintain awareness of this notice until all required actions have been completed in your organisation

6. Contact reference person

Should you require any further information or support concerning this issue, please contact:

Customer Service:

Contact: Hélène Sauvage

FAX: +44 (0)1494 524650

Telephone: +44 (0)1494 532761

E-mail: orders.uk@teleflex.com



Please be advised that all European Economic Area/Switzerland (EEA/CH) and Turkey Member State Competent Authorities to which Teleflex distribute directly will be notified by Teleflex.

Teleflex is committed to providing high quality, safe and effective products. We sincerely apologize for any inconvenience this action may cause your operations. If you have any other questions, feel free to contact your local sales representative or Customer Service.

For and on behalf of Teleflex,

Karen Boylan

Karen Boylan
VP Global RA/QA

Customer No. _____

Appendix 1

FIELD SAFETY CORRECTIVE ACTION ACKNOWLEDGEMENT FORM

PRODUCT FIELD ACTION BY TELEFLEX - IMMEDIATE ATTENTION REQUIRED

RETURN COMPLETED FORM IMMEDIATELY TO:

FAX: +44 (0)1494 524650

E-mail: orders.uk@teleflex.com

<input type="checkbox"/> We confirm receipt of this FSN and completed the required actions contained therein. We confirm that our inventory does NOT include products affected by this Field Action.	<input type="checkbox"/> We confirm receipt of this FSN and completed the required actions contained therein. We confirm our inventory does include products affected by this Field Action. The use and further distribution of the affected products is stopped. All products are put on hold and the amount below will be returned. Return Authorisation No _____
---	---

PLEASE PRINT PRODUCT QUANTITY NUMBERS CLEARLY.

COMMERCIAL NAME:	HUDSON RCI® Nebulizer Adaptor				
Product Number	Lot Number (S)	Quantity	Product Number	Lot Number (S)	Quantity
031-28			041-33		
031-28F			041-35		
031-33			044-28		
031-33J			044-28C		
037-28			044-28F		
037-28C			044-33		
037-28F			044-35		
037-33			044-70		
037-35			403128		
037-39			403133		
037-39C			403728		
037-70			404128		
041-28			404428		
041-28C					

*** Include a copy of the completed Acknowledgement form in the returns, package with the returned units**

*** Ensure the RAN number is clearly visible on the returns package.**

*** Please label returns as "Field Action Returns"**

Complete this Acknowledgement form and return immediately by using the fax number or e-mail address above.

INSTITUTION NAME (EG NAME OF HOSPITAL, HEALTH CARE ORGANISATION)	
INSTITUTION ADDRESS	Phone / Fax
FORM COMPLETED BY:	TITLE/ROLE
PRINT NAME: _____ SIGNATURE: _____	
DATE	

Appendix 2 - Page 1 of 2

Material	Batch	Material	Batch	Material	Batch	Material	Batch	Material	Batch	Material	Batch	Material	Batch
031-28	02A1202382	031-28	02L1200927	037-28	004130	037-28	053120	037-28	097120	037-28C	039130	037-33	117130
	02A1202383		02M1200585		005130		062130		098120		055120		121120
	02A1300194		02M1200749		006130		063130		102130		061130		123120
	02A1300457		02M1201693		007130		064120		103130		071130		157120
	02B1201069	031-28F	02E1200717		010130		064130		104130		073120	172120	
	02C1301862		02E1202197		011130		066130		110130		076130	177120	
	02C1301863		02F1200962		015130		067120		111130		093120	001220	
	02C1301864		02G1200665		016130		067130		112130		099130	002220	
	02D1200247	031-33	02K1201947		017130		068120		113130		103120	004220	
	02D1200248		02A1202384		018130		069120		114130		105120	005220	
	02D1200249		02A1300458		019130		070120		117130		121130	006220	
	02D1201944		02B1300718		020130		071120		118130		142120	007220	
	02D1202233		02D1302731		021130		072120		119130		162120	065120	
	02D1202234		02E1200718		022130		073130		129120		169120	002330	
	02D1202236		02E1202198		023120		074130		130120		170120	004320	
	02D1202274		02F1200963		024120		075120		131120		045140	005320	
	02D1202733		02G1200666		024130		075130		133120		085130	008320	
	02D1202734		02J1202240		025130		076120		134120		106120	009320	
	02D1202735		02M1200584		026130		077120		138120		116130	010320	
	02D1300567		02M1200748		027130		077130		139120		119120	016320	
	02D1300568	02M1201692	028130		078120		141120		120140		006320		
	02D1300864	02M1201771	030120		078130		145120		128140		007320		
	02D1301191	031-33J	02B1201342		031120		079120		146120		129130	005220	
	02D1301192		02B1300717		032130		080120		147120		140120	007220	
	02D1301655		02B1301203		033130		081120		151120		143120	003133	
	02D1302730		02D1202258		036130		082120		152120		161120	004133	
	02E1302765		02D1202259		040120		083120		153120		165120	006123	
	02F1200961		02D1202260		040130		084120		157120		015130	006133	
	02F1300739		02D1202261		041120		085120		159120		032130	007123	
	02F1301285		02E1201279		041130		089130		160120		036130	011133	
	02F1301742		02E1201563		042120		090120		166120		040130	012133	
	02F1302062		02E1203866		042130		090130		167120		049120	013133	
	02F1302232		02E1301554		049120		091120		172120		067120	016123	
	02F1302233		02F1201179		050120		091130		173120		074120	017123	
	02G1200664	02J1201473	050130		092120		174120		089130		018123		
	02G1200676	02J1202736	051120		092130		177120		094120		021133		
	02G1200678	02M1200057	051130		094120		037-28C		003130		101130	023133	
	02G1201016	02M1200747	052120		095120				012130		102130	025133	
	02G1201698	037-28	002130		052130				034130		113120	026123	

Material	Batch	Material	Batch	Material	Batch	Material	Batch	Material	Batch	Material	Batch	Material	Batch
041-28	026133	041-28	070123	041-33	064123	044-28	064124	044-33	037134	403728	035130	404428	009134
	027123		071123		066133		065124		045124		038130		019134
	027133		072123		085123		066124		045134		049130		025134
	028123		074123	091123	073124		050124		054130		035134		
	031133		075123	001223	074124		052134		060130		039134		
	032133		076123	001233	076124	057134	072130	041124					
	034123		080123	002223	077124	060124	100130	044134					
	035123		081123	003223	081124	064124	104120	046124					
	037133		083123	003233	083124	077124	114120	049134					
	038133		084123	006134	084124	084124	115130	056134					
	039123		088123	008124	008134	008134	120120	060134					
	039133		089123	011124	009124	009124	128130	061134					
	040123		090123	011134	018134	018134	132120	080124					
	042133		007133	012124	020124	020124	142130	085124					
	043133		008123	012134	026134	026134	144120						
	044133	015123	013124	035124	035124	155120							
	045123	022123	013134	048124	048124	158120							
	045133	022133	014124	055134	055134	164120							
	046123	028133	016134	062124	062124	001234							
	047123	030133	017134	078124	078124	001234							
	048123	033123	023134	003134	003134	02E1200719	005133						
	050133	040133	024134	004144	004144	02E1200720	029133						
	051133	042123	029134	010144	010144	02E1201281	035133						
	053123	066123	030134	017144	017144	02E1201808	048133						
	056123	067133	032124	022144	022144	02E1203097	051123						
	057123	086123	032134	030144	030144	02F1200964	052123						
	058123	021123	033124	040124	040124	02G1300256	053133						
	058133	025133	033134	049124	049124	02G1301048	055123						
	059133	029123	036134	050134	050134	02K1201946	056133						
	060133	036123	037124	063124	063124	02M1201691	060123						
	061133	041133	037134	067124	067124	02E1201282	063133						
	062123	042133	038124	079124	079124	02F1200965	065123						
	062133	048123	039124	004134	004134	02F1302063	068123						
	063123	051133	045134	007134	007134	02K1201948	068133						
	064123	052133	051134	018124	018124	02L1201194	076133						
	064133	053123	052134	019124	019124	02M1200230	077123						
	065133	058123	057134	033124	033124	008130	082123						
	066133	058133	060124	033134	033134	013130	083133						
	069123	062133	061124	034124	034124	020140	087123						
						023130	404428	002134					
								003144					