### CHAPTER 14

# THE GROUPING AND ZEROING RANGE INTRODUCTION

1401. **General**. Although grouping and zeroing (G&Z) may be carried out on most ranges, it is often expedient to include a G&Z range as part of a range complex to enable this task to be carried out concurrently with other shooting practices. The recommended distance for G&Z of rifles and the LSW is 100 m.

1402. **Aim.** This chapter describes the construction requirements for G&Z ranges and in particular:

a.	Introduction	1401 - 1402
b.	Range danger areas	1403
C.	Siting	1404 - 1405
d.	Construction	1406 - 1409
e.	Communications	1410
f.	Maintenance	1411

#### **RANGE DANGER AREAS**

1403. The RDA requirements for a G&Z range are:

a. **WDA**. When open ground is used with or without a fall of shot bank (see paragraph 1407), the WDA template shown at Figure 19-2 is applied to each firing point. See Figure 14-1.

b. **LDA.** If the range is constructed to Gallery criteria using a mantlet and stop butt, the GR RDA may be applied. See Figure 14-2.

#### SITING

1404. **Requirements.** A reasonably flat, northerly orientated, well drained site, about 120 m long is required. The width of the range depends on the number and width of the firing lanes.

1405. **Lane Width.** The lane width is normally 6 m but this may be reduced to 4 m to reduce ground works and if insufficient land is available.

### CONSTRUCTION

1406. **General**. A G&Z range is shown in outline at Figure 14-1. The construction has been specifically designed to provide a cost effective, single task range.

1407. **Fall of Shot Bank**. Typically a 1.5-2.5 m high bank is provided only to indicate fall of shot.

1408. Targetry. Zeroing screens or AMS may be used.


1409. **Firing Points**. Firing points are required to allow firing from all postures. They should be raised 450 mm above the range floor with a fall of 1:12 to the rear (see Figure 2-13). Fire trenches may be included to extend the use of the range. Figure 2-13 shows a standard firing point.

# COMMUNICATIONS

1410. A means of summoning the emergency services, ideally a land laid telephone, is to be available.

## MAINTENANCE

1411. Ranges with a Gallery RDA template must be maintained to the full GR standard (see Chapter 15).



Any Copies of this Document, either Paper or Electronic are Uncontrolled JSP 403 Volume 2 Edition 3 Change 6

